

MINI 10 YEAR INTERCONNECTED

SMOKE ALARM

MODEL NUMBER:

AJ-770SI4

The Watchman Mini 10 Year Wireless Interconnected Smoke Alarm can connect up to 22 alarms which provides greater protection and early detection throughout the home. When one alarm activates, all other connected alarms will activate.

The alarm contains cutting-edge, split-spectrum technology. Split-spectrum allows the alarm to make more accurate readings inside the sensing chamber by using two optical lights and wavelengths, and along with the additional insect mesh, helps reduce the potential of nuisance alarms caused from environmental factors. The alarm also contains a quick and automated pairing process and connects with the Watchman Wall Controller for simpler functionality. Smoke alarms are designed to be installed in bedrooms, dining rooms, living areas and hallways.



SIMPLE AUTOMATED
INTERCONNECTING



SPLIT-SPECTRUM
TECHNOLOGY




WALL CONTROLLER
AVAILABLE



2 LAYERS OF
INSECT MESH



ALL PACKAGING IS
100% RECYCLABLE



PRODUCT & TECHNICAL SPECIFICATIONS:

Product Size:	78mm x 57mm
Gross Weight:	0.11kg
Sound:	85dB at 3 meters
Humidity:	95% RH
Standby Current:	< 10uA
Alarm Current:	< 60mA
Optimal Temperature Range:	-10 to +50
RF Frequency:	433MHz

FEATURES:

- » Built-in 10 Year 3v lithium battery
- » Automated RF pairing process
- » Split-spectrum technology
- » 9 minute hush
- » Wall Controller available
- » Easy to install
- » 10 year warranty
- » EN14604:2005 certified
- » NZ Building Code, NZS4514:2021 and RTA compliant

WIRELESS

RELAY SWITCH

MODEL NUMBER:

AJ-K102

The Watchman Relay Switch is a low voltage, innovative solution that allows you to integrate Watchman smoke and heat alarms into any existing home security system or isolate power on a particular circuit.

With its advanced technology, the receiver provides a comprehensive and seamless solution for monitoring smoke and fire risks in your home.

The Relay Switch can connect multiple smoke and heat alarms using just one relay switch; this allows for easy connection of all the alarms in the network to the existing home security alarm panel, eliminating the need for multiple receivers.



SIMPLE AUTOMATED
INTERCONNECTING



ALL PACKAGING IS
100% RECYCLABLE



PRODUCT & TECHNICAL SPECIFICATIONS:

Product Size:	55 x 40 x 20mm
Weight:	18.7g
Working Voltage:	DC 6-36V
Channels:	1
Standby Current:	< 1 mA
Alarm Current:	< 40 mA
Receiver Sensitivity:	13dBm
Wireless Frequency:	433 MHz
Output Mode:	Switching Signal (Dry Contact)
Working Mode:	Momentary / Toggle / Latching
Max Load of Relay Contact:	7A

FEATURES:

- » RF technology and connects with all Watchman wireless models.
- » Low Voltage
- » Only require one Relay Switch/interface to connect all alarms in a network
- » Interconnectable with up to 21 alarms

WIRELESS

WALL CONTROLLER

MODEL NUMBER:

AJ-R1063

The Watchman Wall Controller is a portable wireless remote controller which can connect to the Watchman AJ-770SI4 and AJ-770T4 smoke and heat alarms. The Wall Controller functions provide a more convenient way to control your interconnected alarm system and will help if your alarms are not very accessible.

The AJ-R1063 is compatible with older Watchman models; AJ-760SI and AJ-965TU4.




PRODUCT & TECHNICAL SPECIFICATIONS:

Product Size:	75mm x 16mm
Gross Weight:	0.04kg
Certifications:	UKCA-RED, CD-RED, EMC



SIMPLE AUTOMATED
INTERCONNECTING

ALL PACKAGING IS
100% RECYCLABLE



FEATURES:

- » **TEST:** Allows you to test any alarm in a network for 10-15 seconds
- » **LOCATE:** Helps to quickly identify the originally activated alarm. This feature will silence all alarms in the network, apart from the originally activated alarm - which will continue to sound
- » **HUSH:** Silence all alarms within the network. As a safety measure, the originally activated alarm contains a memory function and will emit 3 beeps per minute until silenced from the alarm or pressing the 'TEST' button on the controller
- » RF technology and connects with Watchman wireless alarms
- » DC 3V (2 x AAA batteries - Replaceable)
- » Easy to install
- » Wall bracket for convenient placement