



PEL Series 1

Event Logger



Key Features

800 Users

Stores 5,000 events with date & time stamping

Monitor up to 8 Presco PAC-controllers

Control up to 16 doors

USB 2.0 Mini B interface

The Presco™ Event Logger makes programming multiple Presco™ door access controllers a breeze, providing a user friendly platform for access control with full upload/download capabilities directly from your PC.

Maximum security is provided with 3 different operator levels for programming, editing user details or simply viewing events. When an event is logged it is locked into memory and cannot be manipulated, so you know the integrity of your access control system is assured.

Features

12 Volt D.C. operation.

36 month manufacturer's warranty.

800 Users with names up to 32 characters.

Stores 5,000 events with time & date stamping.

Up to 8 Presco™ PAC controllers can be monitored simultaneously giving control of up to 16 doors.

Internal replaceable button cell holds memory and keeps clock running for up to 10 years.

USB 2.0 Mini B interface to PC.

PC software supplied for Windows™ 7, 8.1 & 10

Three software operator levels restricts access to programming features.

Operating Voltage
10 - 15 Volts D.C.

Operating Current
80 mA. @ 12 Volts D.C.

Operating Temperature
0° to 50°C

Supported Controllers
Series 1 to Series 3 PAC & PAC2 Controllers

PC Interface
USB 2.0 Mini B

Dimensions
104mm x 72mm x 27mm

Weight
150g

REDLITE
SECURITY ELECTRONICS LTD

P O BOX 78-207, Grey Lynn
Auckland, New Zealand
sales@redlite.co.nz

Available From: